

HD1-PR5 Specification

Bluetooth Headset with PTT



- Working Temp: $-20^{\circ}\text{C} \pm 2^{\circ}\text{C} \sim 50^{\circ}\text{C} \pm 2^{\circ}\text{C}$
- Size: 86mm *20mm *25mm
- Weight: 12g
- Bluetooth Ver: 4.1 + EDR
- Status: Dual color LED
- Noise Canceling: DSP, CVC6.0
- Profile: HFP, HSP, A2DP
- Pairing code: 0000
- Charging: 5 Vdc (std.)
- Battery: 90mAh
- Talk Time: 8 Hours (MAX)
- Standby: 220 Hours (MAX)
- Charging Time: 2 Hours
- Frequency: 2.4 - 2.483GHz
- Functions: PTT, Battery Low
- Color: Black / Gray

Package:

<i>item</i>	<i>description</i>	<i>QTY</i>
1	HD1-PR5	1pcs
2	USB charging cable	1pcs
3	Extension earpiece	1pcs
4	Black hook	1pcs
5	Transparent hook	1pcs
6	Silicon bud	1pcs



HD1-PR5



- 1. Port for Charging and Extension earpiece
- 2. PTT Button
- 3. Medical grade silicone ear bud
- 4. Microphone



- 9. Volume control



- 5. High quality Ear hook
- 6. Bluetooth Antenna
- 7. Multi-function button
(Power Button / Pairing Button)
- 8. LED indicator



HD1-PR5 User Manual for Kenwood

1. Make sure that HD1-PR5 is turned off before entering the pairing mode.
Press and hold the multi-function button on HD1-PR5 until the LED flashing blue and red alternately.
HD1-PR5 is now under pairing mode. The device name is 'HD1'.
(Note: Do not release the multi-function button before entering the pairing mode)
2. While selecting 'Connect' on the Kenwood radio to connect with HD1-PR5, you can hear the incoming call's melody in HD1-PR5 within a few seconds.
Press the multi-function button on HD1-PR5, and you will hear the 'Connected'. Now Kenwood radio has successfully connected to HD1-PR5.
(If you don't press the phone multi-function button while the melody of the incoming call, you can't use the HD1-PR5 with the Kenwood radio)
3. Note: If you want to turn off and on HD1-PR5 and Kenwood radio in a short time (within 20 seconds), you need to turn off HD1-PR5 first.
4. To reconnect HD1-PR5 with Kenwood radio:
Note: If you want to reconnect HD1-PR5 to the Kenwood radio when both are turned off, you must turn on the Kenwood radio first.
(When you press the multi-function button once, but it didn't reconnect. press multi-function button again)
 - When HD1-PR5 disconnect with Kenwood radio:
In the first disconnection, press the multi-function button once then you hear 'Connecting'.
In the next and coming disconnections, press the multi-function button twice (each interval one second) then you can hear 'Connecting'.
 - When HD1-PR5 is on (never off after connection):
Turning on Kenwood radio, you will hear 'Connecting' from HD1-PR5 in a few seconds. Press the multi-function button.
 - When Kenwood radio is on:
Turning on HD1-PR5, it will automatically reconnect with Kenwood radio and you can hear 'Connecting' from it.

Now Kenwood radio and HD1-PR5 are successfully reconnected.

